

- Glass X-Ray Tube



Glass X-Ray Tube with Oil Insulation

Specs:

Model No	Nominal Tube Voltage(KVp)	Tube Current(mA)	Focal Spot Size(mm)	Filament Voltage(V)	Filament Current(A)	Compatible Machine Model
XC1-20/200	200	20	$\phi 10$	6	8	XXY-2020
XC8-15/200	200	15	4.0x4.0	6	8	XXY-2020

Model No	Nominal Tube Voltage(KVp)	Tube Current(mA)	Focal Spot Size(mm)	Filament Voltage(V)	Filament Current(A)	Compatible Machine Model
XC3-7/250	250	7	3.5×3.5	4	4	XXY-2507
XC24-5/200	200	5	3.0×3.0	4	4	XX-2005
XC25-5/250	250	5	3.0×3.0	4	4	XX-2505
XC27-15/250	250	15	4.0×4.0	6	8	XX-2515

Glass X-Ray Tube with Air Insulation

Specs:

Model No	Nominal Tube Voltage(KVp)	Tube Current(mA)	Focal Spot Size(mm)	Filament Voltage(V)	Filament Current(A)	Compatible Machine Model
XC40A-5/100	100	5	1.0×1.0	3.4-4.5	4	XXQ-1005
XC40B-5/100	100	5	1.0×1.0	3.4-4.5	4	XXH-1005

Model No	Nominal Tube Voltage(KVp)	Tube Current(mA)	Focal Spot Size(mm)	Filament Voltage(V)	Filament Current(A)	Compatible Machine Model
XC40C-5/100	100	5	1.0×1.0	3.4-4.5	4	XXHz-1005
XC39A-5/160	160	5	1.0×1.0	3.4-4.5	4	XXQ-1605
XC39B-5/160	160	5	1.0×1.0	3.4-4.5	4	XXH-1605
XC39C-5/160	160	5	1.0×1.0	3.4-4.5	4	XXHz-1605
XC18-5/200	200	5	1.5×1.5	3.4-4.5	4	XXQ-2005
XC31A-5/200	200	5	1.0×3.4	3.4-4.5	4	XXH-2005
XC31-5/200	200	5	1.0×3.5	3.4-4.5	4	XXHz-2005
XC28-5/250	250	5	2.0×2.0	6-7	4	XXQ-2505
XC29-5/250	250	3	1.0×2.4	6-7	4	XXH-2505
XC37-5/250	250	5	1.0×2.5	6-7	4	XXHz-2505
XC35-300	300	5	3.5×3.5	6-7	4	XXQ-3005

Model No	Nominal Tube Voltage(KVp)	Tube Current(mA)	Focal Spot Size(mm)	Filament Voltage(V)	Filament Current(A)	Compatible Machine Model
5/300						
XC36-5/300	300	5	1.0×3.5	6-7	4	XXH-3005
XC38-5/300	300	5	1.0×3.5	6-7	4	XXHz-3005
XC44-5/350	350	5	3.5×3.5	6-7	4	XXQ-3505
XC45-5/350	350	5	1.0×3.5	6-7	4	XXH-3505
XC46-5/350	350	5	1.0×3.5	6-7	4	XXHz-3505